Robertson® WORLDWIDE
INNOVATIVE LIGHTING SOLUTIONS

SP48356B1

Ballast Type:	Electromagnetic	Starting Method:	Preheat Start	Unit Color:	Raw
Input Voltage:	230VAC +5%,-10%	Lamp Connection:	Series	Unit Weight:	0.70 lbs.
Input Frequency:	50-60Hz				

ELECTRICAL SPECIFICATIONS:

Line Voltage (V)	Lamp Type	Lamp Watts	No. of Lamps	Line Current (A)	Input Power (W)	Power Factor	Max Current THD (%)	Current Crest Factor	Ballast Factor	Wiring Diagram
230	CFT9W/G23* CFQ9W/G23	9	1	0.15	11	≥ 0.40	≤ 15	≤ 1.6	0.85	101
230	CFT7W/G23	7	1	0.16	11	≥ 0.40	≤ 15	≤ 1.6	0.90	101

* Primary Lamp Type

PERFORMANCE:
- Electromagnetic Reactor Type Ballast
- Preheat Start
- Series Operation
- Normal Power Factor
- Normal Ballast Factor
- Clamped Core & Coil
- Sound Rated A

APPLICATION:
- Maximum Case Temperature: 194ºF/90ºC
- Maximum Ambient Temperature: 104ºF/40ºC
- Minimum Starting Temperature: 0ºF/-18ºC
- Remote Mounting: 10 ft. Max. Lead Length, 18AWG
- Class B Insulation System: 130ºC

SAFETY/STANDARDS:
- No PCB's
- RoHS Compliant

SKU INFORMATION:
- 3P10082 (Version 1 - Leads Out One End)

CASE STYLE: 2X



L	W	H	M	S
3 1/16	1 5/16	1 12/16	2 3/4	3/16
3.07	1.32	1.72	2.75	0.19
7.78 cm	3.34 cm	4.34 cm	6.99 cm	0.48 cm

WIRING DIAGRAM: 101



Ballast lead connections are interchangeable.

- Black: (2) 8" Tolerance: +1.00, -0.50"
- Strip: 0.375" ± 0.060

WARRANTY:
Robertson Worldwide warrants to the purchaser that this ballast will be free from defects in material or workmanship for a period of 2 years from date of manufacture when properly installed and under normal condition of use. For more information on Robertson Worldwide ballasts, visit www.robertsonlighting.com Specifications subject to change without notice.