

UV Ballast to Lamp Graph (425mA)

2/1 lamps

1 lamp

For Preheat Lamps

For Instant Start Lamps

425mA (SO) Ballasts

PSM2GPH18MVDW	Arc voltage	24V-96V	Input voltage	120V-277V (+/-10%)
	2/1 Lamp watts	11W-25W	1 Lamp watts	34W-38W
	Input voltage			

PAQ264G6MV	Arc voltage	92V-176V	Input voltage	100V-240V (+/-10%)
	2/1 Lamp watts	41W-75W		
	Input voltage			

PAQ230G6MV	Arc voltage	28V-100V	Input voltage	100V-240V (+/-10%)
	2/1 Lamp watts	12W-43W		
	Input voltage			

PAQ164G6MV	Arc voltage	92V-176V	Input voltage	100V-240V (+/-10%)
	1 Lamp watts	41W-75W		
	Input voltage			

EZ24-PSM1GPH18DW24	Arc voltage	16V-41V	Input voltage	19.2V-31.2Vac/Vdc
	1 Lamp watts	8W-17W		
	Input voltage			

RSN1GPH20120	Arc voltage	24V-47V	Input voltage	120V only
	1 Lamp watts	10W-20W		
	Input voltage			

IAQ230G6MV	Arc voltage	28V-100V	Input voltage	100V-240V (+/-10%)
	2/1 Lamp watts	12W-43W		
	Input voltage			

IAQ264G6MV	Arc voltage	92V-176V	Input voltage	100V-240V (+/-10%)
	2/1 Lamp watts	39W-75W		
	Input voltage			

IAQ164G6MV	Arc voltage	92V-176V	Input voltage	100V-240V (+/-10%)
	1 Lamp watts	39W-75W		
	Input voltage			

REI164G6MV	Arc voltage	40V-176V	Input voltage	120V-277V (+/-10%)
	1 Lamp watts	17W-75W		
	Input voltage			